



Phone FAQ

To Access Voicemail

- 1. Dial *17
- 2. Follow voicemail prompts.

To Dial Long Distance

- 1. Dial 91 and the number you are dialing out to.
- 2. Wait for a tone. This tone signifies it is waiting for a long distance code.
- 3. Type in your code (without the 16 if your code starts with a 16).
- 4. Press the # key.

To Conference

- 1. You must be on a call to initiate a conference call
- 2. Press **Conf** (button under the word call in the display). This puts your active call on
- 3. Dial the Phone number you would like to Conference (91248XXXXXXX)
- 4. Press **Conf** again to start the conference call

To add a new contact to your phone (9608G only)

- 1. Press the CONTACTS key. Use the left/right keys to select your *Personal* directory.
- 2. To add a contact, press New. To edit a contact, highlight it and press Edit.
 - Use the ▲ up/down ▼ keys to switch between number and name entry.
 - When the name and number have been entered as required, press Save.

How to forward a voicemail to another extension.

- 1. Dial *17 and log into your voicemail
- 2. Press 2 to get voicemails
- 3. Navigate to the message you want to forward
- 4. To Listen press 05. To Forward press 1
- 6. To Forward with Comment press 2
- 7. Type in the Extension and press pound. Press pound again.
- 8. Press Pound again.

9608G only.

- 1. Click on the Mail Button on the Phone.
- 2. Select Listen.
- 3. Select the message.
- 4. Select More.5. Select Copy.
- 6. Select Send To.
- 7. Type in the Extension number and Select Add.
- 8. Highlight the number and Select Send.

Transfer calls Directly to Someone's Voicemail (9608G only)

- 1. With a call connected, press the Message key.
- 2. Dial the extension number of the user or group and press Select.

Making a call

- 1. Lift handset or press Speaker II
- 2. Press the digits on the dial pad (outside calls must start by dialing 9 and then the number). The phone initiates the call after the numbers have been dialed.

Answering a call

A slow flashing appearance button indicates an alerting call. This may also be accompanied by ringing and by the message lamp flashing. If you are currently not on a call:

- To quiet the ringing, press **Ignore**. The call will continue alerting visually.
- To redirect the call to your mailbox, press To VM if shown.
- To answer the call using the handset, lift the handset.
- To answer the call handsfree, press the **II SPEAKER** key.
- To activate mute, press the MUTE key. The button will be lit while mute is active.
- To switch mute off, press the MUTE key again.

Once you have answered the call, you can switch between different talk modes:

- To switch to using the handset, simply lift the handset.
- To switch to handsfree, press the **II SPEAKER** key. If you were using the handset you can now replace it.

Ending a call

- The **Drop** button can be used to end the currently highlighted call.
- If the call is on the phone's speaker, the **II SPEAKER** key is lit. Pressing the key again will end the call.
- If the call is on the phone's handset, replacing the handset will end the call.

To Transfer a call

- 1. Press Transfer
- 2. Dial the Extension of the person you wish to transfer to
- 3. Press Complete (button under the word call in the display).

To put a call on hold and take a call off hold

- 1. To put your current call on hold, press the Hold soft key or the call's appearance button.
- 2. The held call will be indicated by its call appearance button with a fast-flashing green lamp.
- 3. Press the fast-flashing green lamp button to pick up the held call.
- 4. While held, the caller will hear music on hold.
- 5. You can scroll the display using the ▲ up and down ▼ arrow keys. The held call will appear with a icon.